



Senstar ONVIF Server
8
Installation Guide



Contents

| | |
|---|---|
| Introduction..... | 3 |
| Installation..... | 4 |
| Install the Senstar ONVIF Server..... | 4 |
| Configuration..... | 5 |
| Configure the Senstar ONVIF Server..... | 5 |
| Legal information..... | 6 |

Introduction

The Senstar ONVIF Server for the Senstar Symphony Server streams live and historical video from the Senstar Symphony Server as ONVIF Profile S and Profile G streams.

After you install the Senstar ONVIF Server, third-party applications can use ONVIF discovery to detect cameras that are available on the Senstar Symphony Server.

Installation

Install the Senstar ONVIF Server on the computer that hosts the Senstar Symphony Server.

Install the Senstar ONVIF Server

1. On the computer that hosts the Senstar Symphony Server, download and run the Senstar ONVIF Server installer.
2. Accept the license agreement and click **Next**.
3. In the **Username** field, type the username for a Senstar Symphony user with permission to view cameras.
4. In the **Password** field, type the password for the Senstar Symphony user.
5. In the **Listening Port** field, type an unassigned port number (1025 to 65535).
6. Click **Install**.
7. Click **Finish**.
8. Confirm that the `AI ONVIF Server` service is started.

Configuration

Use the manual configuration editor in the Senstar Symphony Client interface to modify the username, password, and port that the Senstar ONVIF Server uses.

Configure the Senstar ONVIF Server

1. In the Senstar Symphony Client interface, click **Server > Manual Configuration Editor**.
2. Click **Add a new setting**.
3. Enter the following values:

```
Type=Server, Section=Main, ID=server_id, Key=ONVIFServerUsername, Value=user_name  
Type=Server, Section=Main, ID=server_id, Key=ONVIFServerPassword, Value=encrypted_password  
Type=Server, Section=Main, ID=server_id, Key=ONVIFServerPort, Value=port_number
```

4. Click **OK**.
5. Click **Close**.
6. Restart the Senstar Symphony Server.

Legal information

Copyright © 2023 Senstar Corporation and/or its Licensor(s). All rights reserved.

This material is for informational purposes only. Senstar makes no warranties, express, implied or statutory, as to the information in this document.

Complying with all applicable copyright laws is the responsibility of the user. Without limiting the rights under copyright, no part of this document may be reproduced, stored in or introduced into a retrieval system, or transmitted in any form or by any means (electronic, mechanical, photocopying, recording, or otherwise), or for any purpose, without the express written permission of Senstar Corporation

Senstar may have patents, patent applications, trademarks, copyrights, or other intellectual property rights covering subject matter in this document. Except as expressly provided in any written license agreement from Senstar, the furnishing of this document does not give you any license to these patents, trademarks, copyrights, or other intellectual property.

Senstar and the Senstar logo are registered trademarks of Senstar Corporation.

All other trademarks are the property of their respective owners.